



# SERVICE BULLETIN # 00023

201 INDUSTRIAL BOULEVARD • KEARNEYSVILLE, WV 25430

Phone: (304) 728-7056 • Fax: (304) 725-6579 • Toll Free: (800) 931-9214

PAGE: 1 of 1

DATE: 6-19-02

REVISION: 07

**SUBJECT:** Dual (2) Price Kit Installation

**MODELS:** All Electro-Mechanical Venders



The following areas of this vender contain voltage, which can cause serious injury or even death. The main power cord, supplying 110 VAC to the evaporator, EMI filter, and refrigeration system. The power line from the EMI filter to the ballast and transformer. The ballast can produce upwards of 600 volts. Remove power from vender before working in any of these areas.

**KIT NUMBER**

**KIT DESCRIPTION**

010149


Standard Dual-Price Kit (2 Price) for RVCC and RVDP Models

012169

Standard Dual-Price Kit (2 Price) for RVMC and RVCD Models

**IMPORTANT NOTE WHEN ORDERING:** Kit #012169 only applies to RVMC and RVCD models with the "Large" select Switch (S.N. 1218XX-XXXX and greater). If you have the "Small" switch use kit #010149.

**Note:** This kit will need a dual price coin changer (not included in kit).



Large Switch



Small Switch

## REASON FOR KIT:

This kit will enable the vender to use two different vend prices.

## INSTRUCTIONS:


1. Unplug Vender
2. Remove terminals for positions 3 & 7 from changer socket and tape ends (See illust.).
3. Insert wire #3 into changer socket position 3. Remove terminal from common of select switch #3 and push the other end of wire #3 in it's place.
4. Insert wire #4 into changer socket position 4. Remove terminal from common of select switch #8 on 8-select venders, (#5 on 5-select venders, #6 on 6-select venders, #7 on 7-select venders, #10 on 10-select venders) and push the other end of wire #4 in it's place.
5. On venders with a sequencer, remove wire #230 from the normally closed position of select switch #1 and wire #115 from the normally open position from select switch #1. Cut off both terminals and strip both wires leaving approximately 3/16" of bare wire at the end. Using one of the enclosed terminals terminate both wires together. (Note: It would be advised to use needle nosed pliers when applying the terminal.) After both wires are terminated securely (see diagram), re-insert wires 230/115 into the normally open position of select switch #1.
6. Tape the ends of all loose, un-insulated terminals.
7. Use plastic wire tie straps to tie the kit harness to the existing harness.
8. SET PRICE SWITCHES IN COIN CHANGER PER INSTRUCTIONS FOR CHANGER.

**-- DO NOT REMOVE VEND RELAY -**

-- 1st price line will give you the price for selections 1, 2 & 3 for all 5, 6, 7, 8, and 10-select venders.

-- 2nd price line will give you the price for all the remaining selections.

**Note:** Place individual price decals on each product identification flavor strip and slide strip into place.



**ANY QUESTIONS??? CONTACT ROYAL VENDORS' CUSTOMER SERVICE DEPARTMENT  
CALL TOLL FREE (800) 931-9214**