



SERVICE BULLETIN # 00056

201 INDUSTRIAL BOULEVARD • KEARNEYSVILLE, WV 25430

Phone: (304) 728-7056 • Fax: (304) 725-6579 • Toll Free: (800) 931-9214

PAGE: 1 of 1

DATE: 8-17-00

REVISION: 02

SUBJECT: Conversion from a Version 2.00 Control Board to Version 5.XX Control Board

MODELS: Merlin 2000

KIT NUMBER

KIT DESCRIPTION

BEFORE WORKING ON VENDER: Remove power from vender by unplugging vender's main power cord from the AC voltage power source (wall outlet).

INSTRUCTIONS:

When converting from a version 2.00 to a version 5.XX control board, use the (2) interface harnesses included with control board.

1. Version 5.XX interface - Motors (842065)

This part has a 15-way posted header and a 15-way female terminal. Connect existing main door harness onto the posted header side of jumper, keyed positions in their proper place. Plug 15-way female terminal onto newly installed version 5.XX control board, keying also in their proper positions.

2. Version 5.XX interface - Validator (842066)

This part has an 11-way posted header and an 11-way female terminal. Plug existing harness on desired validator that is already Merlin compatible onto 11-way posted header. Find validator position on version 5.XX control board and plug in. Be sure both ends are in their proper keyed positions.

**ANY QUESTIONS??? CONTACT ROYAL VENDORS' CUSTOMER SERVICE DEPARTMENT
CALL TOLL FREE (800) 931-9214**